

TECHNICAL DATA

Fluke 362 Clamp Meter



Key features

- Thin, light, compact body design for one-hand operation
- 18mm triangular jaw allows for easy measurement on small cables
- Large, easy-to-read backlit display
- 200 A ac and dc current and 600 V ac and dc voltage measurement range
- 3000 Ω resistance range, continuity detection
- Zero function allows the display to be cleared for DC measurements
- Data Hold function
- CAT III 600 V safety rating

Product overview: Fluke 362 Clamp Meter

Lightweight, thin and compact, the new 362 Fluke Clamp Meter is designed to fit easily in your pocket. The small 18 mm triangular jaw allows access into tight places where other clamp meters can't reach, while providing the accuracy you can trust from a Fluke tool. This durable clamp meter is a must-have for basic maintenance clamp measurements.

Specifications: Fluke 362 Clamp Meter

	Range	Resolution	Accuracy
AC current	200A	0.1A	2% $\pm$ 5 digits (45-65Hz) 2.5% $\pm$ 5 digits (65-400Hz)
DC current	200A	0.1A	2% $\pm$ 5 digits

AC voltage	600 V	0.1 V	1.5% ± 5 digits (45-400Hz)
DC voltage	600 V	0.1 V	1% ± 5 digits
Resistance	300/3000Ω	0.1/1Ω	1% ± 5 digits
Continuity	<=70Ω		
General Specifications			
Size (LxWxH) mm		205 × 60 × 22	
Clamp opening		18 mm	
Weight		196 g	
Safety rating		CAT III 600 V	
Warranty		2 years	

Fluke. *Keeping your world up and running.®*

Fluke Corporation
PO Box 9090, Everett, WA 98206 U.S.A.

For more information call:
In the U.S.A. (800) 443-5853
In Canada (800) 36-FLUKE
From other countries +1 (425) 446-5500
www.fluke.com

©2023 Fluke Corporation.
Specifications subject to change without notice.
02/2023

**Modification of this document is not permitted
without written permission from Fluke Corporation.**